SLLS052G - AUGUST 1987 - REVISED APRIL 2003

- Meet or Exceed the Requirements of TIA/EIA-422-B, TIA/EIA-485-A[†] and **ITU Recommendation V.11**
- High-Speed Advanced Low-Power Schottky Circuitry
- **Designed for 25-Mbaud Operation in Both** Serial and Parallel Applications
- Low Skew Between Devices ... 6 ns Max
- Low Supply-Current Requirements ... 30 mA Max
- Individual Driver and Receiver I/O Pins With Dual V_{CC} and Dual GND
- Wide Positive and Negative Input/Output **Bus Voltage Ranges**
- Driver Output Capacity . . . ±60 mA
- **Thermal Shutdown Protection**
- **Driver Positive- and Negative-Current** Limiting
- Receiver Input Impedance . . . 12 k Ω Min •
- Receiver Input Sensitivity ... ±200 mV Max
- Receiver Input Hysteresis . . . 60 mV Typ
- **Operate From a Single 5-V Supply**
- **Glitch-Free Power-Up and Power-Down** Protection

description/ordering information

The SN65ALS180 and SN75ALS180 differential driver and receiver pairs are integrated circuits designed for bidirectional data communication on multipoint bus-transmission lines. They are designed for balanced transmission lines and meet TIA/EIA-422-B, TIA/EIA-485-A, and ITU Recommendation V.11.

TA	PACKAGE [†]		ORDERABLE PART NUMBER	TOP-SIDE MARKING
	PDIP (N)	Tube of 25	SN75ALS180N	SN75ALS180N
0°C to 70°C	SOIC (D)	Tube of 50	SN75ALS180D	7541 \$190
		Reel of 2500	SN75ALS180DR	73AL3100
–40°C to 85°C	SOIC (D)	Tube of 50	SN65ALS180D	6541 \$190
	301C (D)	Reel of 2500	SN65ALS180DR	03AL3100

ORDERING INFORMATION

[†] Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at www.ti.com/sc/package.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

[†] These devices meet or exceed the requirements of TIA/EIA-485-A, except for the Generator Contention Test (para. 3.4.2) and the Generator Current Limit (para. 3.4.3). The applied test voltage ranges are -6 V to 8 V for the SN75ALS180 and -4 V to 8 V for the SN65ALS180.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.



Copyright © 2003, Texas Instruments Incorporated

SN75ALS180 D OR N PACKAGE (TOP VIEW)						
NC [RE [DE [GND [GND [1 2 3 4 5 6 7	14 13 12 11 10 9 8	V _{CC} V _{CC} A B Z Y			

SN65ALS180...D PACKAGE

NC - No internal connection

SLLS052G – AUGUST 1987 – REVISED APRIL 2003

description/ordering information (continued)

The SN65ALS180 and SN75ALS180 combine a 3-state differential line driver and a differential input line receiver, both of which operate from a single 5-V power supply. The driver and receiver have active-high and active-low enables, respectively, that can be connected together externally to function as a direction control. The driver differential outputs and the receiver differential inputs are connected to separate terminals for greater flexibility and are designed to offer minimum loading to the bus when the driver is disabled or $V_{CC} = 0$.

These ports feature wide positive and negative common-mode voltage ranges, making the device suitable for party-line applications.

Function Tables						
DRIVER						
INPUT	ENABLE	OUT	PUTS			
D	DE	Y	Z			
Н	Н	Н	L			
L	Н	L	Н			
Х	L	Z	Z			

R	Ε	С	E	IV	Ε	R
R	Ε	С	E	IV	Е	R

DIFFERENTIAL INPUTS A–B	ENABLE RE	OUTPUT R
$V_{ID} \ge 0.2 V$	L	Н
$-0.2 \text{ V} < \text{V}_{\text{ID}} < 0.2 \text{ V}$	L	?
$V_{ID} \leq -0.2 V$	L	L
Х	н	Z
Open	L	н

H = high level, L = low level, ? = indeterminate, X = irrelevant, Z = high impedance (off)

logic diagram (positive logic)





SLLS052G - AUGUST 1987 - REVISED APRIL 2003

schematics of inputs and outputs







SLLS052G - AUGUST 1987 - REVISED APRIL 2003

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)[†]

Supply voltage, V _{CC} (see Note 1)	
Voltage range at any bus terminal	
Enable input voltage, V _I	5.5 V
Package thermal impedance, θ_{JA} (see Notes 2 and 3):	D package
	N package 80°C/W
Operating virtual junction temperature, T _J	
Lead temperature 1,6 mm (1/16 inch) from case for 10	seconds
Storage temperature range, T _{st}	

[†] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. All voltage values, except differential I/O bus voltage, are with respect to network ground terminal.

- 2. Maximum power dissipation is a function of $T_J(max)$, θ_{JA} , and T_A . The maximum allowable power dissipation at any allowable ambient temperature is $P_D = (T_J(max) T_A)/\theta_{JA}$. Operating at the absolute maximum T_J of 150°C can affect reliability.
- 3. The package thermal impedance is calculated in accordance with JESD 51-7.

MIN NOM MAX UNIT 4.75 5.25 Vcc Supply voltage 5 V 12 v VI or VIC Voltage at any bus terminal (separately or common mode) -7 D, DE, and RE V High-level input voltage 2 ۷ін D, DE, and RE V Low-level input voltage 0.8 VIL ±12 V VID Differential input voltage (see Note 4) -60 Driver mΑ ЮН High-level output current Receiver -400 μΑ Driver 60 Low-level output current **IOL** mΑ Receiver 8 SN65ALS180 -40 85 °С TA Operating free-air temperature SN75ALS180 0 70

recommended operating conditions

NOTE 4: Differential-input/output bus voltage is measured at the noninverting terminal, A/Y, with respect to the inverting terminal, B/Z.



SLLS052G - AUGUST 1987 - REVISED APRIL 2003

DRIVERS

electrical characteristics over recommended ranges of supply voltage and operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS [†]		MIN	түр‡	MAX	UNIT
VIK	Input clamp voltage	lj = -18 mA				-1.5	V
VO	Output voltage	I _O = 0		0		6	V
IVOD1	Differential output voltage	I <mark>O</mark> = 0		1.5		6	V
	Differential output voltage	R _L = 100 Ω,	See Figure 1	1/2 V _{OD1} or 2§			V
_		R _L = 54 Ω,	See Figure 1	1.5	2.5	5	
V _{OD3}	Differential output voltage	$V_{test} = -7 V \text{ to } 12 V,$	See Figure 2	1.5		5	V
$\Delta V_{OD} $	Change in magnitude of differential output voltage¶	R _L = 54 Ω or 100 Ω,	See Figure 1			±0.2	V
Voc	Common-mode output voltage	R _L = 54 Ω or 100 Ω,	See Figure 1			3 –1	V
Δ V _{OC}	Change in magnitude of common-mode output voltage¶	R _L = 54 Ω or 100 Ω,	See Figure 1			±0.2	V
		Output disabled	V _O = 12 V			1	mA
10	Oulput current	(see Note 5)	$V_{O} = -7 V$			-0.8	IIIA
ЧН	High-level input current	V _I = 2.4 V				20	μΑ
١ _{IL}	Low-level input current	V _I = 0.4 V				-400	μA
		$V_{O} = -6 V$	SN75ALS180			-250	
		$V_{O} = -4 V$	SN65ALS180			-250	
los	Short-circuit output current#	V _O = 0	All			-150	mA
		VO = VCC	All			250	
		V _O = 8 V	All			250	
ICC	Supply current	No load	Driver outputs enabled, Receiver disabled		25	30	mA
			Outputs disabled		19	26	

[†] The power-off measurement in TIA/EIA-422-B applies to disabled outputs only and is not applied to combined inputs and outputs.

[‡] All typical values are at V_{CC} = 5 V, $T_A = 25^{\circ}C$.

§ The minimum V_{OD2} with 100- Ω load is either 1/2 V_{OD2} or 2 V, whichever is greater.

 $\int \Delta |V_{OC}|$ and $\Delta |V_{OC}|$ are the changes in magnitude of V_{OD} and V_{OC} , respectively, that occur when the input is changed from a high level to a low level.

[#] Duration of the short circuit should not exceed one second for this test.

NOTE 5: This applies for both power on and off; refer to TIA/EIA-485-A for exact conditions. The TIA/EIA-422-B limit does not apply for a combined driver and receiver terminal.

switching characteristics over recommended ranges of supply voltage and operating free-air temperature

PARAMETER		TEST CONDITIONS			MIN	TYP‡	MAX	UNIT
^t d(OD)	Differential output delay time	$R_L = 54 \Omega$,	C _L = 50 pF,	See Figure 3	3	8	13	ns
	Pulse skew ($ t_{d(ODH)} - t_{d(ODL)} $)	$R_{L} = 54 \ \Omega,$	C _L = 50 pF,	See Figure 3		1	6	ns
^t t(OD)	Differential output transition time	$R_{L} = 54 \ \Omega,$	C _L = 50 pF,	See Figure 3	3	8	13	ns
^t PZH	Output enable time to high level	RL = 110 Ω,	See Figure 4			23	50	ns
^t PZL	Output enable time to low level	RL = 110 Ω,	See Figure 5			19	24	ns
^t PHZ	Output disable time from high level	R _L = 110 Ω,	See Figure 4			8	13	ns
^t PLZ	Output disable time from low level	R _L = 110 Ω,	See Figure 5			8	13	ns

[‡] All typical values are at $V_{CC} = 5$ V and $T_A = 25^{\circ}C$.

SLLS052G – AUGUST 1987 – REVISED APRIL 2003

SYMBOL EQUIVALENTS						
DATA-SHEET PARAMETER	TIA/EIA-422-B	TIA/EIA-485-A				
VO	V _{oa} , V _{ob}	V _{oa} , V _{ob}				
IVOD1	Vo	Vo				
IVOD2	V _t (R _L = 100 Ω)	$V_t (R_L = 54 \Omega)$				
V _{OD3}		V _t (test termination measurement 2)				
V _{test}		V _{tst}				
	$ V_t - \overline{V}_t $	$ V_t - \overline{V}_t $				
V _{OC}	V _{os}	V _{os}				
$\Delta V_{OC} $	$ V_{OS} - \overline{V}_{OS} $	$ V_{OS} - \overline{V}_{OS} $				
los	IIsal, IIsbl					
IO	$ _{xa} , _{xb} $	l _{ia} , l _{ib}				

RECEIVERS

electrical characteristics over recommended ranges of common-mode input voltage, supply voltage, and operating free-air temperature (unless otherwise noted)

PARAMETER		TE	ST CONDITIONS	MIN	TYP†	MAX	UNIT
V _{IT+}	Positive-going input threshold voltage	V _O = 2.7 V,	I _O = -0.4 mA			0.2	V
V _{IT-}	Negative-going input threshold voltage	V _O = 0.5 V,	I _O = 8 mA	-0.2‡			V
V _{hys}	Hysteresis voltage (V _{IT+} – V _{IT} –)				60		mV
VIK	Enable-input clamp voltage	lı = -18 mA				-1.5	V
∨он	High-level output voltage	V _{ID} = 200 mV,	$I_{OH} = -400 \ \mu A$, See Figure 6	2.7			V
VOL	Low-level output voltage	$V_{ID} = -200 \text{ mV},$	I _{OL} = 8 mA, See Figure 6			0.45	V
loz	High-impedance-state output current	V_{O} = 0.4 V to 2.4 V				±20	μA
		Other input = 0 V	V _I = 12 V			1	~ ^
'I	Line input current	(see Note 6)	$V_{I} = -7 V$			-0.8	IIIA
ЧΗ	High-level enable-input current	V _{IH} = 2.7 V				20	μA
ЧL	Low-level enable-input current	V _{IL} = 0.4 V				-100	μA
r _i	Input resistance			12			kΩ
IOS	Short-circuit output current	V _{ID} = 200 mV,	$V_{O} = 0$	-15		-85	mA
Icc	Supply current	No load	Receiver outputs enabled, Driver inputs disabled		19	30	mA
			Outputs disabled		19	26	

[†] All typical values are at $V_{CC} = 5 \text{ V}$, $T_A = 25^{\circ}\text{C}$.

[‡] The algebraic convention, in which the less positive (more negative) limit is designated minimum, is used in this data sheet for common-mode input voltage and threshold voltage levels only.

NOTE 6: This applies for both power on and power off. Refer to TIA/EIA-485-A for exact conditions.



SLLS052G - AUGUST 1987 - REVISED APRIL 2003

switching characteristics over recommended ranges of supply voltage and operating free-air temperature

	PARAMETER	TEST CONDI	TEST CONDITIONS		TYP†	MAX	UNIT
^t PLH	Propagation delay time, low- to high-level output	$V_{ID} = -1.5 V$ to 1.5 V, See Figure 7	C _L = 15 pF,	9	14	19	ns
^t PHL	Propagation delay time, high- to low-level output	$V_{ID} = -1.5 V$ to 1.5 V, See Figure 7	C _L = 15 pF,	9	14	19	ns
	Skew (tp _{HL} – tp _{LH})	$V_{ID} = -1.5 V$ to 1.5 V, See Figure 7	C _L = 15 pF,		2	6	ns
^t PZH	Output enable time to high level	C _L = 15 pF,	See Figure 8		7	14	ns
^t PZL	Output enable time to low level	C _L = 15 pF,	See Figure 8		7	14	ns
^t PHZ	Output disable time from high level	C _L = 15 pF,	See Figure 8		20	35	ns
^t PLZ	Output disable time from low level	C _L = 15 pF,	See Figure 8		8	17	ns

[†] All typical values are at V_{CC} = 5 V, T_A = 25°C.

PARAMETER MEASUREMENT INFORMATION



Figure 1. Driver $V_{\mbox{OD}}$ and $V_{\mbox{OC}}$



Figure 2. Driver V_{OD3}



SLLS052G - AUGUST 1987 - REVISED APRIL 2003

PARAMETER MEASUREMENT INFORMATION



NOTES: A. CL includes probe and jig capacitance.

B. The input pulse is supplied by a generator having the following characteristics: PRR \leq 1 MHz, 50% duty cycle, t_f \leq 6 ns, t_f \leq 8 ns, t_f \leq 8





NOTES: A. CL includes probe and jig capacitance.

B. The input pulse is supplied by a generator having the following characteristics: PRR \leq 1 MHz, 50% duty cycle, t_f \leq 6 ns, t_f \leq 6 ns, Z_O = 50 Ω .

Figure 4. Driver Test Circuit and Voltage Waveforms



NOTES: A. Cl includes probe and jig capacitance.

B. The input pulse is supplied by a generator having the following characteristics: PRR \leq 1 MHz, 50% duty cycle, t_f \leq 6 ns, t_f \leq 6 ns, Z_O = 50 Ω .





SLLS052G - AUGUST 1987 - REVISED APRIL 2003

PARAMETER MEASUREMENT INFORMATION



Figure 6. Receiver VOH and VOL



- NOTES: A. CL includes probe and jig capacitance.
 - B. The input pulse is supplied by a generator having the following characteristics: PRR \leq 1 MHz, 50% duty cycle, t_f \leq 6 ns, t_f \leq 6 ns, Z_O = 50 Ω .

Figure 7. Receiver Test Circuit and Voltage Waveforms



SLLS052G - AUGUST 1987 - REVISED APRIL 2003



PARAMETER MEASUREMENT INFORMATION

NOTES: A. CL includes probe and jig capacitance.

B. The input pulse is supplied by a generator having the following characteristics: PRR \leq 1 MHz, 50% duty cycle, t_f \leq 6 ns, t_f \leq 6 ns, Z_O = 50 Ω .

Figure 8. Receiver Test Circuit and Voltage Waveforms



SLLS052G - AUGUST 1987 - REVISED APRIL 2003



TYPICAL CHARACTERISTICS – DRIVERS



Figure 11



SLLS052G - AUGUST 1987 - REVISED APRIL 2003



TYPICAL CHARACTERISTICS – RECEIVERS



SLLS052G - AUGUST 1987 - REVISED APRIL 2003



TYPICAL CHARACTERISTICS – RECEIVERS

APPLICATION INFORMATION



NOTE A: The line should terminate at both ends in its characteristic impedance (R_T = Z_O). Stub lengths off the main line should be kept as short as possible.

Figure 18. Typical Application Circuit



N (R-PDIP-T**)

PLASTIC DUAL-IN-LINE PACKAGE

16 PINS SHOWN



NOTES:

- A. All linear dimensions are in inches (millimeters).B. This drawing is subject to change without notice.
- Falls within JEDEC MS-001, except 18 and 20 pin minimum body length (Dim A).
- \triangle The 20 pin end lead shoulder width is a vendor option, either half or full width.



D (R-PDSO-G14)

PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0.006 (0,15).

D. Falls within JEDEC MS-012 variation AB.



IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address:

Texas Instruments

Post Office Box 655303 Dallas, Texas 75265

Copyright © 2004, Texas Instruments Incorporated